

Ambrose 'One' Preamp 'A30' Tube Mono Blocks ModWright Instruments, Inc.



Ambrose One

Resolution, dynamics, three-dimensionality, holographic soundstage and organic tonality all come together in the 'One'.

FEATURES:

- Full dual mono design with external power supply.
- Dual power umbilicals.
- Dual tube power rectifiers.
- Transformer coupled inputs and outputs.
- RCA and XLR (fully balanced) inputs and outputs.
- Remote control volume and mute.
- Home Theater Bypass.
- Pure Class A, fully balanced, zero negative feedback.
- Dovetail Joined Hardwood and AL Billet enclosure.

SPECIFICATIONS:

- Gain: ~11db.
- Input impedance: 20K
- Output Impedance: 100 ohm
- Frequency Response: 20Hz – 100Khz (-1dB)
- (2) 6922/7308 driver tubes
- (2) 5AR4/GZ34/5R4GYS/5U4G/5U4GB rectifiers
- Dimensions: 17"W x 12.5"D x 4.5"H
- Weight: 33lb

Ambrose A30 Mono Blocks

The A30 tube mono blocks offer 30W of pure Class A, SE power, with zero global feedback.

FEATURES:

- 30W Class A, SE power.
- Zero negative feedback.
- Hand wound SE output transformers.
- Point to point signal path wiring.
- Dovetail Joined Hardwood and AL Billet enclosure.
- Single triode input gain stage.
- Single Ended parallel Pure Pentode power stage.

SPECIFICATIONS:

- Power: 32W Class A into 6 ohms @.1% THD
- Input impedance: 100K
- Gain: 22dB
- Frequency Response: 20Hz – 20Khz
- SS High, low noise high voltage rectifiers
- Fixed Bias (no maintenance)
- (1)12AT7 driver tube / amp
- (3) EL34 power tubes / amp
- Dims: 9"W x 17"D x 10"H
- Weight: 53lb per amp



ModWright Instruments
Express. Simplicity. Truth.

